

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Safety relay for emergency stop and safety doors up to SILCL 1, Cat. 1, PL c, depending on the application up to SILCL 3, Cat. 4, PL e, 1-channel operation, automatic start, 1 enabling current path,  $U_S$  = 24 V DC, fixed screw terminal block

### Your advantages

- Depending on the application, up to Cat. 4/PL e according to ISO 13849-1, SILCL 3 according to IEC 62061

- 1 enabling current path, 1 digital signal output
- Automatic activation



### **Key Commercial Data**

Packing unit	1 pc
GTIN	4 046356 904988
GTIN	4046356904988
Weight per Piece (excluding packing)	69.000 g
Custom tariff number	85371098
Country of origin	Germany

### Technical data

#### Note

Utilization restriction	EMC: class A product, see manufacturer's declaration in the download area
-------------------------	---

#### **Dimensions**

Width	6.8 mm
Height	93.1 mm
Depth	102.5 mm



### Technical data

### Ambient conditions

Ambient temperature (operation)	-40 °C 60 °C (observe derating)
Ambient temperature (storage/transport)	-40 °C 85 °C
Max. permissible relative humidity (operation)	75 % (on average, 85% infrequently, non-condensing)
Max. permissible humidity (storage/transport)	75 % (on average, 85% infrequently, non-condensing)
Maximum altitude	≤ 2000 m (Above sea level)

### Power supply

Rated control circuit supply voltage U <sub>S</sub>	24 V DC -15 % / +10 %
	20.4 V DC 26.4 V DC
Rated control supply current I <sub>S</sub>	typ. 42 mA
Power consumption at U <sub>S</sub>	typ. 1 W
Inrush current	$4.5$ A ( $\Delta t$ < 120 μs at $U_s$ )
Filter time	1 ms (at A1 in the event of voltage dips at U <sub>s</sub> )
Protective circuit	Surge protection Suppressor diode
	Protection against polarity reversal for rated control circuit supply voltage

### Digital inputs

Input voltage range "0" signal	0 V DC 5 V DC (for safe Off; at S12)
Input current range "0" signal	0 mA 2 mA (for safe Off; at S12)
Inrush current	< 20 mA (with U <sub>s</sub> /I <sub>x</sub> to S12)
	< 10 mA (with U <sub>s</sub> /I <sub>x</sub> at the start circuit)
Current consumption	< 5 mA (with U <sub>s</sub> /I <sub>x</sub> to S12)
	< 10 mA (with U <sub>s</sub> /I <sub>x</sub> at the start circuit)
Filter time	max. 1.5 ms (at S12; test pulse width)
	min. 7.5 ms (at S12; test pulse rate)
	Test pulse rate = 5 x Test pulse width
Voltage at input/start and feedback circuit	24 V DC -15 % / +10 %
Max. permissible overall conductor resistance	150 Ω

### Relay outputs: enabling current path

Output name	Enabling current path
Output description	safety-related N/O contacts
Number of outputs	1 (undelayed)
Contact type	1 enabling current path
Contact material	AgSnO <sub>2</sub>
Switching voltage	min. 12 V AC/DC
	max. 250 V AC/DC (Observe the load curve)
Limiting continuous current	6 A (observe derating)
Inrush current	min. 3 mA
	max. 6 A
Sq. Total current	36 A <sup>2</sup> (observe derating)
Switching capacity	min. 60 mW



### Technical data

### Relay outputs: enabling current path

Switching frequency	max. 0.5 Hz
Mechanical service life	10x 10 <sup>6</sup> cycles
Output fuse	6 A gL/gG (N/O contact)
	4 A gL/gG (for low-demand applications)

### Alarm outputs

Output description	non-safety-related
Number of outputs	1 (digital, PNP)
Voltage	22 V DC (U <sub>s</sub> - 2 V)
Current	max. 100 mA
Maximum inrush current	500 mA ( $\Delta t$ = 1 ms at U <sub>s</sub> )
Short-circuit protection	no

#### Times

Typical pickup time at US	< 250 ms (when controlled via A1)
Typical response time at US	< 175 ms
Typical release time at US	< 20 ms (when controlled via A1 or S12)
Recovery time	< 500 ms

### General

Relay type	Electromechanical relay with forcibly guided contacts in accordance with IEC/EN 61810-3 (EN 50205)
Nominal operating mode	100% operating factor
Net weight	69 g
Mounting position	vertical or horizontal
Mounting type	DIN rail mounting
Assembly instructions	See derating curve
Degree of protection	IP20
Min. degree of protection of inst. location	IP54
Housing material	РВТ
Housing color	yellow
Operating voltage display	1 x green LED
Status display	2 x green LEDs

### Connection data

Connection method	Screw connection
pluggable	no
Conductor cross section solid min.	0.2 mm²
Conductor cross section solid max.	2.5 mm²
Conductor cross section flexible min.	0.2 mm <sup>2</sup>
Conductor cross section flexible max.	2.5 mm <sup>2</sup>
Conductor cross section AWG min.	26
Conductor cross section AWG max.	12



### Technical data

### Connection data

Stripping length	12 mm
Screw thread	M3

### Safety-related characteristic data

Stop category	0	
Designation IEC 61508 - High demand		
Safety Integrity Level (SIL)	1 (up to SIL 3 depending on the application)	
Designation	IEC 61508 - Low demand	
Safety Integrity Level (SIL)  1 (up to SIL 3 depending on the application)		
Designation EN ISO 13849		
Performance level (PL)	c (up to PL e depending on the application)	
Category	1 (up to Cat. 4 depending on the application)	
Designation	EN 62061	
Safety Integrity Level Claim Limit (SIL CL)	1 (up to SILCL 3 depending on the application)	

### Standards and Regulations

Designation	Air clearances and creepage distances between the power circuits
Standards/regulations	DIN EN 50178
Rated insulation voltage	250 V AC
	250 V AC
Rated surge voltage/insulation	Safe isolation, reinforced insulation 6 kV between input circuit and enabling current path Basic insulation 4 kV between all current paths and housing
Degree of pollution	2
Overvoltage category	III
Shock	15g
Vibration (operation)	10 Hz150 Hz, 2g
Conformance	CE-compliant


### **Environmental Product Compliance**

China RoHS	Environmentally Friendly Use Period = 50	
	For details about hazardous substances go to tab "Downloads", Category "Manufacturer's declaration"	


### Drawings



### Block diagram




### Block diagram



- Key: 1 = Voltage limitation
- 3 = Control circuit channel 1
- 4 = Control circuit signal output
- 5 = Start channel 1 and 2
- 6 = Control circuit channel 2
- K1, K2 = Force-guided elementary relays

### Application drawing



### Classifications

### eCl@ss

eCl@ss 5.1	27371900
eCl@ss 6.0	27371800
eCl@ss 7.0	27371819
eCl@ss 8.0	27371819
eCl@ss 9.0	27371819

### **ETIM**

ETIM 5.0	EC001449
ETIM 6.0	EC001449



### Classifications

**UNSPSC** 

EAC [FI]  RU C- DE.A*30.B.01082	UNSPSC 13.2		39121501	
Approvals  UL Listed / cUL Listed / Functional Safety / EAC / cULus Listed  Ex Approvals  Approval details  UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  CUL Listed thttp://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety  EAC FILE E 140324	Approvals			
UL Listed / Functional Safety / EAC / cULus Listed  Ex Approvals  Approval details  UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  cUL Listed cult http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety 44-205-13755202  EAC FILE  RU C-DE.A*30.B.01082	Approvals			
UL Listed / Functional Safety / EAC / cULus Listed  Ex Approvals  Approval details  UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  cUL Listed cult http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety 44-205-13755202  EAC FILE  RU C-DE.A*30.B.01082	Approvale			
Ex Approvals  Approval details  UL Listed  Listed  http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  cUL Listed  cUL Listed  http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety  EAC  EHC  RU C- DE.A*30.B.01082		and Safaty / EAC /	al II va Liotad	
Approval details  UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  cUL Listed output  thtp://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety 44-205-13755202  EAC FILE  RU C-DE.A*30.B.01082	——————————————————————————————————————	onal Salety / EAC /	COLUS LISted	
UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  CUL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety 44-205-13755202  EAC ERI C-DE.A*30.B.01082	Ex Approvals			
UL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  CUL Listed http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety 44-205-13755202  EAC ERI C-DE.A*30.B.01082				
CUL Listed  CUL Listed  http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety  EAC  RU C- DE.A*30.B.01082	Approval details			
CUL Listed  CUL Listed  http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm FILE E 140324  Functional Safety  EAC  RU C- DE.A*30.B.01082				
Functional Safety  EAC  RU C- DE.A*30.B.01082	UL Listed	LISTED	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm	FILE E 140324
Functional Safety  EAC  RU C- DE.A*30.B.01082				
Functional Safety  EAC  RU C- DE.A*30.B.01082	cUL Listed	c (ŪL)	http://database.ul.com/cgi-bin/XYV/template/LISEXT/1FRAME/index.htm	FILE E 140324
EAC [FI]  RU C- DE.A*30.B.01082				
EAC [FI]  RU C- DE.A*30.B.01082				
DE.A*30.B.01082	Functional Safety	FEW WOOD  OF IT WISH (MANUAL PROPERTY OF THE P		44-205-13755202
DE.A*30.B.01082				
	EAC	rar 101		
cllius Listed		LIIL		22 ( 00 1002
Cllus listed (U)				
LISTED	cULus Listed	C <b>(UL)</b> US LISTED		

Phoenix Contact 2018 © - all rights reserved http://www.phoenixcontact.com