SIEMENS

Data sheet

6GK5004-2BD00-1AB2

SCALANCE XB004-2 unmanaged Industrial Ethernet Switch for 10/100 Mbit/s; for setting up small star and line topologies; LED diagnostics, IP20, 24V DC power supply, with 4x 10/100 Mbit/s twisted pair ports with RJ45 sockets; 2x 100 Mbit/s multimode glass FOC port with SC socket; Manual available as a download

product type designation	SCALANCE XB004-2	
transfer rate		
transfer rate	10 Mbit/s, 100 Mbit/s	
interfaces / for communication / integrated		
number of electrical connections		
 for network components or terminal equipment 	4; RJ45	
number of 100 Mbit/s SC ports		
• for multimode	2	
interfaces / other		
number of electrical connections		
• for power supply	1	
type of electrical connection		
• for power supply	3-pole terminal block	
supply voltage, current consumption, power loss		
type of voltage / 1 / of the supply voltage	DC	
 supply voltage / 1 / rated value 	24 V	
• power loss [W] / 1 / rated value	4 W	

 supply voltage / 1 / rated value 	19.2 28.8 V
 consumed current / 1 / maximum 	0.165 A
 product component / 1 / fusing at power supply 	Yes
input	
ambient conditions	
ambient temperature	
during operation	-10 +60 °C
during storage	-40 +80 °C
during transport	-40 +80 °C
relative humidity	
 at 25 °C / without condensation / during 	95 %
operation / maximum	
protection class IP	IP20
design, dimensions and weights design	Box
width	45 mm
	100 mm
height	87 mm
depth	
net weight fastening method	0.165 kg
-	Yes
35 mm top hat DIN rail mounting	
wall mounting	Yes
 S7-1500 rail mounting 	No
product features, product functions, product compo	nents / general
number of automatically learnable MAC addresses	1024
product functions / management, configuration, eng	ineering
product function	
 multiport mirroring 	No
• CoS	Yes
PROFINET conformity class	A
product function / switch-managed	No
product functions / redundancy	
product function	
 Parallel Redundancy Protocol (PRP)/operation in the PRP-network 	Yes
Parallel Redundancy Protocol	No
(PRP)/Redundant Network Access (RNA)	
standards, specifications, approvals	
standard	
• for FM	FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2, GP. IIC, T4

 for hazardous zone 	EN 60079-0:2009, EN60079-15:2010, II 3 G Ex nA IIC T4 Gc, KEMA 07ATEX0145 X
 for safety / from CSA and UL 	UL 60950-1, CSA C22.2 No. 60950-1
 for emitted interference 	EN 61000-6-4 (Class A)
 for interference immunity 	EN 61000-6-2
MTBF	232 у
standards, specifications, approvals / CE	
certificate of suitability / CE marking	Yes
standards, specifications, approvals / other	
certificate of suitability	EN 61000-6-2, EN 61000-6-4
• C-Tick	Yes
 KC approval 	Yes
further information / internet-Links	
Internet-Link	
 to website: Selector TIA Selection Tool 	http://www.siemens.com/snst
 to website: Industrial communication 	http://www.siemens.com/simatic-net
• to website: Industry Mall	https://mall.industry.siemens.com
 to website: Information and Download Center 	http://www.siemens.com/industry/infocenter
• to website: Image database	http://automation.siemens.com/bilddb
 to website: CAx-Download-Manager 	http://www.siemens.com/cax
• to website: Industry Online Support	https://support.industry.siemens.com
security information	
security information	Siemens provides products and solutions with industrial security
	functions that support the secure operation of plants, solutions,
	machines, equipment and/or networks. They are important
	components in a holistic industrial security concept. With this in
	mind, Siemens' products and solutions undergo continuous development. Siemens recommends strongly that you regularly
	check for product updates. For the secure operation of Siemens
	products and solutions, it is necessary to take suitable preventive
	action(e.g. cell protection concept) and integrate each component
	into a holistic, state-of-the-art industrial security concept. Third-
	party products that may be in use should also be considered. For
	more information about industrial security, visit
	http://www.siemens.com/industrialsecurity. To stay informed about
	product updates as they occur, sign up for a product-specific newsletter. For more information, visit
	http://support.automation.siemens.com. (V3.4)
last modified:	10/30/2020