

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Attachment plug with surge voltage coarse and fine protection, for coaxial signal interfaces with floating shield, signal voltage 5 V. Connection: BNC socket/plug

### Why buy this product

- For insertion in the cable



### **Key Commercial Data**

Packing unit	1 STK
GTIN	4 017918 069445
GTIN	4017918069445
Weight per Piece (excluding packing)	114.000 g
Custom tariff number	85363010
Country of origin	Germany

### Technical data

#### **Dimensions**

Height	93 mm
Width	25.4 mm
Length	25.4 mm

### Ambient conditions

Ambient temperature (operation)	-40 °C 80 °C
Degree of protection	IP20

### General



## Technical data

### General

Housing material	Aluminum
Color	black
Standards for cearances and creepage distances	VDE 0110-1
	IEC 60664-1
Mounting type	Connection-specific intermediate plugging
Туре	Attachment plug
Direction of action	Line-Shield/Earth Ground

### Protective circuit

IEC test classification	C2
	C3
	D1
Maximum continuous voltage U <sub>C</sub>	5 V DC
Rated current	185 mA (25 °C)
Operating effective current I <sub>C</sub> at U <sub>C</sub>	≤ 300 μA
Residual current I <sub>PE</sub>	≤ 2 µA
Nominal discharge current I <sub>n</sub> (8/20) µs (line-earth)	10 kA
Nominal discharge current I <sub>n</sub> (8/20) µs (line-shield)	10 kA
Total discharge current I <sub>total</sub> (8/20) µs	20 kA
Output voltage limitation at 1 kV/µs (line-earth) spike	≤ 500 V
Output voltage limitation at 1 kV/µs (line-shield) spike	≤ 35 V
Output voltage limitation at 1 kV/µs (line-shield) static	≤ 15 V
Residual voltage at I <sub>n</sub> (line-shield)	≤ 10 V
Voltage protection level U <sub>p</sub> (line-earth)	≤ 500 V (C1 - 1 kV/500 A)
	≤ 500 V (C3 - 10 A)
Voltage protection level U <sub>p</sub> (line-shield)	≤ 25 V (C3 - 10 A)
	≤ 55 V (C1 - 1 kV/500 A)
Response time t <sub>A</sub> (line-earth)	≤ 100 ns
Response time tA (line-shield)	≤ 500 ns
Input attenuation aE, asym.	typ. 2 dB (≤ 20 MHz)
Cut-off frequency fg (3 dB), asym. (shield) in 50 Ohm system	typ. 90 MHz
Surge protection fault message	none
Impulse durability (line-earth)	C2 - 10 kV/5 kA
	D1 - 2.5 kA

### Connection data

Connection method	BNC 50 Ω
Connection method IN	BNC socket



### Technical data

### Connection data

Connection method OUT	BNC plug	
Connection, equipotential bonding		
Connection method	PVC litz wire	
Standards and Regulations		
Standards/regulations	IEC 61643-21	

# Environmental Product Compliance

Standards/specifications


China RoHS	Environmentally Friendly Use Period = 50
	For details about hazardous substances go to tab "Downloads", Category "Manufacturer's declaration"

IEC 61643-21 2000

IN


## Drawings

### Dimensional drawing





### Circuit diagram



### Classifications

### eCl@ss

eCl@ss 4.0	27140201
eCl@ss 4.1	27130801
eCl@ss 5.0	27130801
eCl@ss 5.1	27130800
eCl@ss 6.0	27130800
eCl@ss 7.0	27130807
eCl@ss 8.0	27130807
eCl@ss 9.0	27130807



### Classifications

### **ETIM**

ETIM 2.0	EC000943
ETIM 3.0	EC000943
ETIM 4.0	EC000943
ETIM 5.0	EC000943
ETIM 6.0	EC000943

### UNSPSC

UNSPSC 6.01	30212010
UNSPSC 7.0901	39121610
UNSPSC 11	39121610
UNSPSC 12.01	39121610
UNSPSC 13.2	39121620

## Approvals

Approvals

Approvals

EAC

Ex Approvals

Approval details

EAC

RU C-DE.A\*30.B01561

### Accessories

Accessories

Flange coupling



### Accessories

Connector/Adapter - BNC-V 50 - 2805041



BNC connector, single-level, for mounting on NS 32 or NS 35/7.5, wave impedance: 50 Ohm

Connector/Adapter - BNC-DV 50 - 2805038



BNC connector, double-level, for mounting on NS 32 or NS 35/7.5, wave impedance: 50 Ohm

Phoenix Contact 2018 @ - all rights reserved http://www.phoenixcontact.com